

Pos. Item Pos.	Ident-Nr. Ident-No N°d'ident	Bezeichnung	Designation Désignation
	53 1206	Gebrauchsanweisung	instruction manual mode d'emploi
	53 5632	Kundendienstschrift (unvollständig)	service manual (incomplete) brochure service (incomplet)
	53 5690	Ergänzung zur Kundendienstschrift	supplement/complément
		Module/Leiterplatten	module, p.c.b./carte
	75 9658	Bedienteil links	front-left/commande à gauche
	75 9659	Bedienteil rechts	front-right/commande à droite
	75 9997	Kopfhörerbuchse	phones
	75 9598	Display	display
		Buchsen	sockets/douilles
	79 5938	Cinch, RC-Bus	
	79 5939	Cinch	
	79 5940	Cinch	
	79 7269	CD Gegenlagergewicht (schwing minimierung)	CD chuck weight (min. oscillution)
		Kabel	cable
	75 9536	Cinch, Ton	cinch, AF/cinch audio
	75 9537	Cinch, Bus	cinch, bus

Pos. Item Pos.	Ident-Nr. Ident-No N°d'ident	Bezeichnung	Designation Désignation
			
D321	70 6829	1N4148	
D331	79 5941	3,9V 0,5W	
D334	70 9579	1N4002	
D335	70 9579	1N4002	
D336	70 9579	1N4002	
D337	70 9579	1N4002	
D340	79 5943	24CBZX 79C 34V	
D341	70 9579	1N4002	
D342	70 9579	1N4002	
D351	70 9579	1N4002	
D352	70 9579	1N4002	
D353	70 9579	1N4002	
D354	70 9579	1N4002	
D355	79 5942	HZS 6 C 2	
			
D401	79 5755	TLHY4405	
D402	79 5755	TLHY4405	
D403	79 5845	TLHY4405 BT12Z	
D404	79 5845	TLHY4405 BT12Z	
D421	79 5755	TLHY4405	
			
L1	79 5931	Netz-Filter 2 x 0,4mHy 2,6A	AC-filter/filtre électrique secteur

Pos. Item Pos.	Ident-Nr. Ident-No N°d'ident	Bezeichnung	Designation Désignation
			
IC1	79 5234	TDA1302T	
IC2	79 5235	TDA1301T	
IC3	79 5944	SAA7345 GP / M5	
IC4	79 5945	TDA7073 A / N2	
IC5	79 5945	TDA7073 A / N2	
IC8	72 7431	NJM4556D oder RC4556NB	
IC8	79 5999	SAA7350GB (Laufwerk)	
IC9	79 6000	RC5532N	
IC10	79 6000	RC5532N	
IC11	79 5950	M38172M4-113 FP	
IC12	79 6001	GL7805GRLTR TO-220	
			
C1	79 5751	3300pF 20% 400V	
			
R294	79 5929	Lautstärke, Kopfhörer	volume, phones
			
KR162	79 5948	16,934 MHz	
KR311	79 5949	4,00 MHz Keramik	Ceramic

Pos. Item Pos.	Ident-Nr. Ident-No N°d'ident	Bezeichnung	Designation Désignation
			
T153	72 2134	BC338-25	
T154	72 2134	BC338-25	
T155	72 2134	BC338-25	
T156	72 2134	BC338-25	
T272	72 2134	BC338-25	
T273	72 3073	BC548B	
T284	72 2134	BC338-25	
T285	72 3073	BC548B	
T321	79 0854	BC558B	
T322	72 3073	BC548B	
T331	79 0854	BC558B	
T338	79 0854	BC558B	
T341	79 5860	BC640	
			
R101	79 0715	4,7 Ohm 1/4W	
R116	73 9449	1,0 Ohm 1/4W 5%	
R121	79 0715	4,7 Ohm 1/4W	
R139	79 0715	4,7 Ohm 1/4W	
R163	79 0715	4,7 Ohm 1/4W	
R171	73 3339	6,8 Ohm 1/4W	
R191	73 3339	6,8 Ohm 1/4W	
R192	73 3339	6,8 Ohm 1/4W	



